

- *: Check the A dimension based on the distance from the mounting surface to the top surface of the table and select accordingly.
- Material/Finish


Material/Finish	₡ RoHS
	NLSDN-N
Main Body	SS400 Ferrosoferric Oxide Film (Black)
Hex Socket Head Cap Screw	SCM435 Ferrosoferric Oxide Film (Black)
Knock Pin	SUS303


- Stoppers for linear guides with threaded holes (fine) and knock pin mounting holes machined.
- In combination with fine screw thread stopper bolts*1, fine adjustment of the screw-in depth is
- Knock pins enable easy main body positioning.
- Supported rail sizes are 15 mm/20 mm/25 mm/30 mm/35 mm.
- Hex socket head cap screws and knock pins for mounting are provided with all products.
- *1: Stopper bolts are not provided. The customer is asked to prepare them.

Application

Table position adjustment Table retention and fall prevention Stoppers for emergencies

Unit : mm																		
Part Number 1	w	ш	Α	В	Ε	F	Р	P1	e	Т	M (Fine)		D	d		Hex Socket Head Cap Screw	Knock Pin	Mass (g)
		П									Nominal of Thread	Pitch		u	LC	nex socket nead cap sciew	(Knock Pin Diameter Tolerance m6)	iviass (g)
NLSDN-01-N	32	30	23.5	18	12	12	16	16	6	25	M6	0.75	5.5	4	6	M5×12	φ4×10	124.8
NLSDN-02-N	32	38	31.5	18	12	12	16	16	6	25	M6	0.75	5.5	4	6	M5×12	φ4×10	149.7
NLSDN-03-N	32	43	35.5	18	12	12	16	16	6	25	M6	0.75	5.5	4	6	M5×12	φ4×10	164.3
NLSDN-04-N	32	35	27.5	18	12	12	16	16	6	25	M8	1.0	5.5	4	6	M5×12	φ4×10	137.5
NLSDN-05-N	32	43	35.5	18	12	12	16	16	6	25	M8	1.0	5.5	4	6	M5×12	φ4×10	162.4
NLSDN-06-N	32	45	37.5	18	12	12	16	16	6	25	M8	1.0	5.5	4	6	M5×12	φ4×10	168.1
NLSDN-07-N	32	40	32.5	23	12	12	18	18	6	32	M8	1.0	6.6	4	6	M6×12	φ4×10	173.6
NLSDN-08-N	32	50	40.5	23	12	12	18	18	6	32	M8	1.0	6.6	4	6	M6×12	φ4×10	203
NLSDN-09-N	32	50	43.5	23	12	12	18	18	6	32	M8	1.0	6.6	4	6	M6×12	φ4×10	203.5
NLSDN-10-N	38	57	49.5	28	16	16	20	20	8	38	M8	1.0	9	5	8	M8×16	φ5×12	363.9
NLSDN-11-N	45	63	55.5	31	16	16	25	25	8	45	M8	1.0	9	5	8	M8×16	φ5×12	510.4







Related Products



• Part Number Specification





Not Available



Not Available

Not Available

Available / Add'l charge



